

Fourier Series

主講者：虞台文

Content

- Periodic Functions
- Fourier Series
- Complex Form of the Fourier Series
- Impulse Train
- Analysis of Periodic Waveforms
- Half-Range Expansion
- Least Mean-Square Error Approximation

Fourier Series

Periodic Functions

The Mathematic Formulation

- Any function that satisfies

$$f(t) = f(t + T)$$

where T is a constant and is called the *period* of the function.

Example:

$$f(t) = \cos \frac{t}{3} + \cos \frac{t}{4} \quad \text{Find its period.}$$

$$f(t) = f(t+T) \longrightarrow \cos \frac{t}{3} + \cos \frac{t}{4} = \cos \frac{1}{3}(t+T) + \cos \frac{1}{4}(t+T)$$

Fact: $\cos \theta = \cos(\theta + 2m\pi)$

$$\begin{array}{l} \frac{T}{3} = 2m\pi \\ \frac{T}{4} = 2n\pi \end{array} \longrightarrow \begin{array}{l} T = 6m\pi \\ T = 8n\pi \end{array} \longrightarrow T = 24\pi \quad \text{smallest } T$$

Example:

$$f(t) = \cos \omega_1 t + \cos \omega_2 t \quad \text{Find its period.}$$

$$f(t) = f(t+T) \quad \longrightarrow \quad \cos \omega_1 t + \cos \omega_2 t = \cos \omega_1 (t+T) + \cos \omega_2 (t+T)$$

$$\omega_1 T = 2m\pi$$

$$\omega_2 T = 2n\pi$$



$$\frac{\omega_1}{\omega_2} = \frac{m}{n}$$




$\frac{\omega_1}{\omega_2}$ must be a
rational number

Example:

$$f(t) = \cos 10t + \cos(10 + \pi)t$$

Is this function a periodic one?




$$\frac{\omega_1}{\omega_2} = \frac{10}{10 + \pi} \quad \text{not a rational number}$$

Fourier Series

Fourier Series

Introduction

- Decompose a periodic input signal into *primitive periodic components*.



Synthesis

$$f(t) = \underbrace{\frac{a_0}{2}}_{\text{DC Part}} + \underbrace{\sum_{n=1}^{\infty} a_n \cos \frac{2\pi n t}{T}}_{\text{Even Part}} + \underbrace{\sum_{n=1}^{\infty} b_n \sin \frac{2\pi n t}{T}}_{\text{Odd Part}}$$

T is a period of all the above signals

Let $\omega_0 = 2\pi/T$.

$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos(n\omega_0 t) + \sum_{n=1}^{\infty} b_n \sin(n\omega_0 t)$$

Orthogonal Functions

- Call a set of functions $\{\phi_k\}$ *orthogonal* on an interval $a < t < b$ if it satisfies

$$\int_a^b \phi_m(t)\phi_n(t)dt = \begin{cases} 0 & m \neq n \\ r_n & m = n \end{cases}$$

Orthogonal set of Sinusoidal Functions

Define $\omega_0 = 2\pi/T$.

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) dt = 0, \quad m \neq 0$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) dt = 0, \quad m \neq 0$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

We now prove this one

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \sin(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \cos(n\omega_0 t) dt = 0, \quad \text{for all } m \text{ and } n$$

Proof

$$\cos \alpha \cos \beta = \frac{1}{2} [\cos(\alpha + \beta) + \cos(\alpha - \beta)]$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt \quad m \neq n$$

$$= \frac{1}{2} \int_{-T/2}^{T/2} \cos[(m+n)\omega_0 t] dt + \frac{1}{2} \int_{-T/2}^{T/2} \cos[(m-n)\omega_0 t] dt$$

$$= \frac{1}{2} \frac{1}{(m+n)\omega_0} \sin[(m+n)\omega_0 t] \Big|_{-T/2}^{T/2} + \frac{1}{2} \frac{1}{(m-n)\omega_0} \sin[(m-n)\omega_0 t] \Big|_{-T/2}^{T/2}$$

$$= \frac{1}{2} \frac{1}{(m+n)\omega_0} \underbrace{2 \sin[(m+n)\pi]}_0 + \frac{1}{2} \frac{1}{(m-n)\omega_0} \underbrace{2 \sin[(m-n)\pi]}_0$$

$$= 0$$

Proof

$$\cos \alpha \cos \beta = \frac{1}{2} [\cos(\alpha + \beta) + \cos(\alpha - \beta)]$$

$$\cos^2 \alpha = \frac{1}{2} [1 + \cos 2\alpha]$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt \quad m = n$$

$$= \int_{-T/2}^{T/2} \cos^2(m\omega_0 t) dt = \frac{1}{2} \int_{-T/2}^{T/2} [1 + \cos 2m\omega_0 t] dt$$

$$= \frac{1}{2} t \Big|_{-T/2}^{T/2} + \underbrace{\frac{1}{4m\omega_0} \sin 2m\omega_0 t \Big|_{-T/2}^{T/2}}_0$$

$$= \frac{T}{2}$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

Orthogonal set of Sinusoidal Functions

an orthogonal set.

Define $\omega_0 = 2\pi/T$.

$$\left\{ \begin{array}{l} 1, \\ \cos \omega_0 t, \cos 2\omega_0 t, \cos 3\omega_0 t, \dots \\ \sin \omega_0 t, \sin 2\omega_0 t, \sin 3\omega_0 t, \dots \end{array} \right\}$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) dt = 0, \quad m \neq 0$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) dt = 0, \quad m \neq 0$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \sin(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \cos(n\omega_0 t) dt = 0, \quad \text{for all } m \text{ and } n$$

Decomposition

$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos(n\omega_0 t) + \sum_{n=1}^{\infty} b_n \sin(n\omega_0 t)$$

$$a_0 = \frac{2}{T} \int_{t_0}^{t_0+T} f(t) dt$$

$$a_n = \frac{2}{T} \int_{t_0}^{t_0+T} f(t) \cos n\omega_0 t dt \quad n = 1, 2, \dots$$

$$b_n = \frac{2}{T} \int_{t_0}^{t_0+T} f(t) \sin n\omega_0 t dt \quad n = 1, 2, \dots$$

Proof

Use the following facts:

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) dt = 0, \quad m \neq 0$$


$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) dt = 0, \quad m \neq 0$$

$$\int_{-T/2}^{T/2} \cos(m\omega_0 t) \cos(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \sin(n\omega_0 t) dt = \begin{cases} 0 & m \neq n \\ T/2 & m = n \end{cases}$$

$$\int_{-T/2}^{T/2} \sin(m\omega_0 t) \cos(n\omega_0 t) dt = 0, \quad \text{for all } m \text{ and } n$$

Example (Square Wave)




$$a_0 = \frac{2}{2\pi} \int_0^\pi 1 dt = 1$$

$$a_n = \frac{2}{2\pi} \int_0^\pi \cos ntdt = \frac{1}{n\pi} \sin nt \Big|_0^\pi = 0 \quad n = 1, 2, \dots$$

$$b_n = \frac{2}{2\pi} \int_0^\pi \sin ntdt = -\frac{1}{n\pi} \cos nt \Big|_0^\pi = -\frac{1}{n\pi} (\cos n\pi - 1) = \begin{cases} 2/n\pi & n = 1, 3, 5, \dots \\ 0 & n = 2, 4, 6, \dots \end{cases}$$

Example (Square Wave)

$$f(t) = \frac{1}{2} + \frac{2}{\pi} \left(\sin t + \frac{1}{3} \sin 3t + \frac{1}{5} \sin 5t + \dots \right)$$





$$a_0 = \frac{2}{2\pi} \int_0^{\pi} 1 dt = 1$$

$$a_n = \frac{2}{2\pi} \int_0^{\pi} \cos ntdt = \frac{1}{n\pi} \sin nt \Big|_0^{\pi} = 0 \quad n = 1, 2, \dots$$

$$b_n = \frac{1}{2\pi} \int_0^{\pi} \sin ntdt = -\frac{1}{n\pi} \cos nt \Big|_0^{\pi} = -\frac{1}{n\pi} (\cos n\pi - 1) = \begin{cases} 2/n\pi & n = 1, 3, 5, \dots \\ 0 & n = 2, 4, 6, \dots \end{cases}$$

$$f(t) = \frac{1}{2} + \frac{2}{\pi} \left(\sin t + \frac{1}{3} \sin 3t + \frac{1}{5} \sin 5t + \dots \right)$$



Harmonics

$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos \frac{2\pi n t}{T} + \sum_{n=1}^{\infty} b_n \sin \frac{2\pi n t}{T}$$

$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos(n\omega_0 t) + \sum_{n=1}^{\infty} b_n \sin(n\omega_0 t)$$

DC Part

Even Part

Odd Part


T is a period of all the above signals

Harmonics

Define $\omega_0 = 2\pi f_0 = \frac{2\pi}{T}$, called the *fundamental angular frequency*.

Define $\omega_n = n\omega_0$, called the *n-th harmonic* of the periodic function.

$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos n\omega_0 t + \sum_{n=1}^{\infty} b_n \sin n\omega_0 t$$




$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos \omega_n t + \sum_{n=1}^{\infty} b_n \sin \omega_n t$$

Harmonics

$$\begin{aligned} f(t) &= \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos \omega_n t + \sum_{n=1}^{\infty} b_n \sin \omega_n t \\ &= \frac{a_0}{2} + \sum_{n=1}^{\infty} (a_n \cos \omega_n t + b_n \sin \omega_n t) \\ &= \frac{a_0}{2} + \sum_{n=1}^{\infty} \sqrt{a_n^2 + b_n^2} \left(\frac{a_n}{\sqrt{a_n^2 + b_n^2}} \cos \omega_n t + \frac{b_n}{\sqrt{a_n^2 + b_n^2}} \sin \omega_n t \right) \\ &= \frac{a_0}{2} + \sum_{n=1}^{\infty} \sqrt{a_n^2 + b_n^2} (\cos \theta_n \cos \omega_n t + \sin \theta_n \sin \omega_n t) \\ &= C_0 + \sum_{n=1}^{\infty} C_n \cos(\omega_n t - \theta_n) \end{aligned}$$

Amplitudes and Phase Angles

$$f(t) = C_0 + \sum_{n=1}^{\infty} C_n \cos(\omega_n t - \theta_n)$$


harmonic amplitude

phase angle

$$C_0 = \frac{a_0}{2}$$

$$C_n = \sqrt{a_n^2 + b_n^2}$$

$$\theta_n = \tan^{-1}\left(\frac{b_n}{a_n}\right)$$

Fourier Series

**Complex Form of the
Fourier Series**

Complex Exponentials

$$e^{jn\omega_0 t} = \cos n\omega_0 t + j \sin n\omega_0 t$$

$$e^{-jn\omega_0 t} = \cos n\omega_0 t - j \sin n\omega_0 t$$

$$\cos n\omega_0 t = \frac{1}{2} \left(e^{jn\omega_0 t} + e^{-jn\omega_0 t} \right)$$

$$\sin n\omega_0 t = \frac{1}{2j} \left(e^{jn\omega_0 t} - e^{-jn\omega_0 t} \right) = -\frac{j}{2} \left(e^{jn\omega_0 t} - e^{-jn\omega_0 t} \right)$$

Complex Form of the Fourier Series

$$\begin{aligned} f(t) &= \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos n\omega_0 t + \sum_{n=1}^{\infty} b_n \sin n\omega_0 t \\ &= \frac{a_0}{2} + \frac{1}{2} \sum_{n=1}^{\infty} a_n (e^{jn\omega_0 t} + e^{-jn\omega_0 t}) - \frac{j}{2} \sum_{n=1}^{\infty} b_n (e^{jn\omega_0 t} - e^{-jn\omega_0 t}) \\ &= \frac{a_0}{2} + \sum_{n=1}^{\infty} \left[\frac{1}{2} (a_n - jb_n) e^{jn\omega_0 t} + \frac{1}{2} (a_n + jb_n) e^{-jn\omega_0 t} \right] \\ &= c_0 + \sum_{n=1}^{\infty} [c_n e^{jn\omega_0 t} + c_{-n} e^{-jn\omega_0 t}] \end{aligned}$$

$$c_0 = \frac{a_0}{2}$$

$$c_n = \frac{1}{2} (a_n - jb_n)$$

$$c_{-n} = \frac{1}{2} (a_n + jb_n)$$

Complex Form of the Fourier Series

$$\begin{aligned} f(t) &= c_0 + \sum_{n=1}^{\infty} \left[c_n e^{jn\omega_0 t} + c_{-n} e^{-jn\omega_0 t} \right] \\ &= c_0 + \sum_{n=1}^{\infty} c_n e^{jn\omega_0 t} + \sum_{n=-\infty}^{-1} c_n e^{jn\omega_0 t} \\ &= \sum_{n=-\infty}^{\infty} c_n e^{jn\omega_0 t} \end{aligned}$$

$$\begin{aligned} c_0 &= \frac{a_0}{2} \\ c_n &= \frac{1}{2}(a_n - jb_n) \\ c_{-n} &= \frac{1}{2}(a_n + jb_n) \end{aligned}$$

Complex Form of the Fourier Series

$$c_0 = \frac{a_0}{2} = \frac{1}{T} \int_{-T/2}^{T/2} f(t) dt$$

$$c_n = \frac{1}{2} (a_n - jb_n)$$

$$= \frac{1}{T} \left[\int_{-T/2}^{T/2} f(t) \cos n\omega_0 t dt - j \int_{-T/2}^{T/2} f(t) \sin n\omega_0 t dt \right]$$

$$= \frac{1}{T} \int_{-T/2}^{T/2} f(t) (\cos n\omega_0 t - j \sin n\omega_0 t) dt$$

$$= \frac{1}{T} \int_{-T/2}^{T/2} f(t) e^{-jn\omega_0 t} dt$$

$$c_{-n} = \frac{1}{2} (a_n + jb_n) = \frac{1}{T} \int_{-T/2}^{T/2} f(t) e^{jn\omega_0 t} dt$$

$$c_0 = \frac{a_0}{2}$$

$$c_n = \frac{1}{2} (a_n - jb_n)$$

$$c_{-n} = \frac{1}{2} (a_n + jb_n)$$


Complex Form of the Fourier Series

$$f(t) = \sum_{n=-\infty}^{\infty} c_n e^{jn\omega_0 t}$$

$$c_n = \frac{1}{T} \int_{-T/2}^{T/2} f(t) e^{-jn\omega_0 t} dt$$

$$c_0 = \frac{a_0}{2}$$
$$c_n = \frac{1}{2}(a_n - jb_n)$$
$$c_{-n} = \frac{1}{2}(a_n + jb_n)$$

If $f(t)$ is real,

 $c_{-n} = c_n^*$

$$c_n = |c_n| e^{j\phi_n}, \quad c_{-n} = c_n^* = |c_n| e^{-j\phi_n}$$

$$|c_n| = |c_{-n}| = \frac{1}{2} \sqrt{a_n^2 + b_n^2}$$

$$\phi_n = \tan^{-1} \left(-\frac{b_n}{a_n} \right)$$

$$n = \pm 1, \pm 2, \pm 3, \dots$$



$$c_0 = \frac{1}{2} a_0$$

Complex Frequency Spectra


$$c_n = |c_n| e^{j\phi_n}, \quad c_{-n} = c_n^* = |c_n| e^{-j\phi_n}$$

$$|c_n| = |c_{-n}| = \frac{1}{2} \sqrt{a_n^2 + b_n^2} \qquad \phi_n = \tan^{-1} \left(-\frac{b_n}{a_n} \right) \quad n = \pm 1, \pm 2, \pm 3, \dots$$

$$c_0 = \frac{1}{2} a_0$$



Example



$$c_n = \frac{A}{T} \int_{-d/2}^{d/2} e^{-jn\omega_0 t} dt$$

$$= \frac{A}{T} \frac{1}{-jn\omega_0} e^{-jn\omega_0 t} \Big|_{-d/2}^{d/2}$$


$$= \frac{A}{T} \left(\frac{1}{-jn\omega_0} e^{-jn\omega_0 d/2} - \frac{1}{-jn\omega_0} e^{jn\omega_0 d/2} \right)$$

$$= \frac{A}{T} \frac{1}{-jn\omega_0} (-2j \sin n\omega_0 d/2)$$

$$= \frac{A}{T} \frac{1}{\frac{1}{2} n\omega_0} \sin n\omega_0 d/2$$

$$= \frac{Ad}{T} \frac{\sin\left(\frac{n\pi d}{T}\right)}{\left(\frac{n\pi d}{T}\right)}$$


Example



$$c_n = \frac{Ad}{T} \frac{\sin\left(\frac{n\pi d}{T}\right)}{\left(\frac{n\pi d}{T}\right)}$$

$$d = \frac{1}{20}, \quad T = \frac{1}{4}, \quad \frac{d}{T} = \frac{1}{5}$$
$$\omega_0 = \frac{2\pi}{T} = 8\pi$$


Example



$$c_n = \frac{Ad}{T} \frac{\sin\left(\frac{n\pi d}{T}\right)}{\left(\frac{n\pi d}{T}\right)}$$

$$d = \frac{1}{20}, \quad T = \frac{1}{2}, \quad \frac{d}{T} = \frac{1}{5}$$
$$\omega_0 = \frac{2\pi}{T} = 4\pi$$

Example



$$c_n = \frac{A}{T} \int_0^d e^{-jn\omega_0 t} dt$$

$$= \frac{A}{T} \frac{1}{-jn\omega_0} e^{-jn\omega_0 t} \Big|_0^d$$

$$= \frac{A}{T} \left(\frac{1}{-jn\omega_0} e^{-jn\omega_0 d} - \frac{1}{-jn\omega_0} \right)$$

$$= \frac{A}{T} \frac{1}{jn\omega_0} (1 - e^{-jn\omega_0 d})$$

$$= \frac{A}{T} \frac{1}{jn\omega_0} e^{-jn\omega_0 d/2} (e^{jn\omega_0 d/2} - e^{-jn\omega_0 d/2})$$


$$= \frac{Ad}{T} \frac{\sin\left(\frac{n\pi d}{T}\right)}{\left(\frac{n\pi d}{T}\right)} e^{-jn\omega_0 d/2}$$

Fourier Series

Impulse Train

Dirac Delta Function

$$\delta(t) = \begin{cases} 0 & t \neq 0 \\ \infty & t = 0 \end{cases} \quad \text{and} \quad \int_{-\infty}^{\infty} \delta(t) dt = 1$$



Also called *unit impulse function*.


Property

$$\int_{-\infty}^{\infty} \delta(t)\phi(t)dt = \phi(0)$$

$\phi(t)$: Test Function

$$\int_{-\infty}^{\infty} \delta(t)\phi(t)dt = \int_{-\infty}^{\infty} \delta(t)\phi(0)dt = \phi(0)\int_{-\infty}^{\infty} \delta(t)dt = \phi(0)$$

Impulse Train



$$\delta_T(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT)$$

Fourier Series of the Impulse Train

$$\delta_T(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT)$$

$$a_0 = \frac{2}{T} \int_{-T/2}^{T/2} \delta_T(t) dt = \frac{2}{T}$$

$$a_n = \frac{2}{T} \int_{-T/2}^{T/2} \delta_T(t) \cos(n\omega_0 t) dt = \frac{2}{T}$$

$$b_n = \frac{2}{T} \int_{-T/2}^{T/2} \delta_T(t) \sin(n\omega_0 t) dt = 0$$

$$\delta_T(t) = \frac{1}{T} + \frac{2}{T} \sum_{n=-\infty}^{\infty} \cos n\omega_0 t$$

Complex Form

Fourier Series of the Impulse Train

$$\delta_T(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT)$$

$$c_0 = \frac{a_0}{2} = \frac{1}{T} \int_{-T/2}^{T/2} \delta_T(t) dt = \frac{1}{T}$$

$$c_n = \frac{1}{T} \int_{-T/2}^{T/2} \delta_T(t) e^{-jn\omega_0 t} dt = \frac{1}{T}$$

$$\delta_T(t) = \frac{1}{T} \sum_{n=-\infty}^{\infty} e^{jn\omega_0 t}$$


Fourier Series

**Analysis of
Periodic Waveforms**

Waveform Symmetry


- Even Functions

$$f(t) = f(-t)$$



- Odd Functions

$$f(t) = -f(-t)$$



Decomposition

- Any function $f(t)$ can be expressed as the sum of an even function $f_e(t)$ and an odd function $f_o(t)$.


$$f(t) = f_e(t) + f_o(t)$$

$$f_e(t) = \frac{1}{2}[f(t) + f(-t)] \quad \text{Even Part}$$


$$f_o(t) = \frac{1}{2}[f(t) - f(-t)] \quad \text{Odd Part}$$

Example


$$f(t) = \begin{cases} e^{-t} & t > 0 \\ 0 & t < 0 \end{cases}$$



$$f_e(t) = \begin{cases} \frac{1}{2}e^{-t} & t > 0 \\ \frac{1}{2}e^t & t < 0 \end{cases}$$




$$f_o(t) = \begin{cases} \frac{1}{2}e^{-t} & t > 0 \\ -\frac{1}{2}e^t & t < 0 \end{cases}$$




Half-Wave Symmetry

$$f(t) = f(t + T) \quad \text{and} \quad f(t) = -f(t + T/2)$$




Quarter-Wave Symmetry

Even Quarter-Wave Symmetry




Odd Quarter-Wave Symmetry




Hidden Symmetry

- The following is a asymmetry periodic function:



- Adding a constant to get symmetry property.




Fourier Coefficients of Symmetrical Waveforms


- The use of symmetry properties simplifies the calculation of Fourier coefficients.
 - Even Functions
 - Odd Functions
 - Half-Wave
 - Even Quarter-Wave
 - Odd Quarter-Wave
 - Hidden

Fourier Coefficients of Even Functions

$$f(t) = f(-t)$$




$$f(t) = \frac{a_0}{2} + \sum_{n=1}^{\infty} a_n \cos n\omega_0 t$$




$$a_n = \frac{4}{T} \int_0^{T/2} f(t) \cos(n\omega_0 t) dt$$

Fourier Coefficients of Even Functions

$$f(t) = -f(-t)$$




$$f(t) = \sum_{n=1}^{\infty} b_n \sin n\omega_0 t$$



$$b_n = \frac{4}{T} \int_0^{T/2} f(t) \sin(n\omega_0 t) dt$$

Fourier Coefficients for Half-Wave Symmetry


$$f(t) = f(t + T) \quad \text{and} \quad f(t) = -f(t + T/2)$$



The Fourier series contains only odd harmonics.

Fourier Coefficients for Half-Wave Symmetry

$$f(t) = f(t + T) \quad \text{and} \quad f(t) = -f(t + T/2)$$




$$f(t) = \sum_{n=1}^{\infty} (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t)$$


$$a_n = \begin{cases} 0 & \text{for } n \text{ even} \\ \frac{4}{T} \int_0^{T/2} f(t) \cos(n\omega_0 t) dt & \text{for } n \text{ odd} \end{cases}$$

$$b_n = \begin{cases} 0 & \text{for } n \text{ even} \\ \frac{4}{T} \int_0^{T/2} f(t) \sin(n\omega_0 t) dt & \text{for } n \text{ odd} \end{cases}$$

Fourier Coefficients for Even Quarter-Wave Symmetry




$$f(t) = \sum_{n=1}^{\infty} a_{2n-1} \cos[(2n-1)\omega_0 t]$$




$$a_{2n-1} = \frac{8}{T} \int_0^{T/4} f(t) \cos[(2n-1)\omega_0 t] dt$$

Fourier Coefficients for Odd Quarter-Wave Symmetry




$$f(t) = \sum_{n=1}^{\infty} b_{2n-1} \sin[(2n-1)\omega_0 t]$$



$$b_{2n-1} = \frac{8}{T} \int_0^{T/4} f(t) \sin[(2n-1)\omega_0 t] dt$$

Example

Even Quarter-Wave Symmetry




$$a_{2n-1} = \frac{8}{T} \int_0^{T/4} f(t) \cos[(2n-1)\omega_0 t] dt = \frac{8}{T} \int_0^{T/4} \cos[(2n-1)\omega_0 t] dt$$

$$= \frac{8}{(2n-1)\omega_0 T} \sin[(2n-1)\omega_0 t] \Big|_0^{T/4} = (-1)^{n-1} \frac{4}{(2n-1)\pi}$$

Example

$$f(t) = \frac{4}{\pi} \left(\cos \omega_0 t - \frac{1}{3} \cos 3\omega_0 t + \frac{1}{5} \cos 5\omega_0 t + \dots \right)$$

Even Quarter-Wave Symmetry




$$a_{2n-1} = \frac{8}{T} \int_0^{T/4} f(t) \cos[(2n-1)\omega_0 t] dt = \frac{8}{T} \int_0^{T/4} \cos[(2n-1)\omega_0 t] dt$$

$$= \frac{8}{(2n-1)\omega_0 T} \sin[(2n-1)\omega_0 t] \Big|_0^{T/4} = (-1)^{n-1} \frac{4}{(2n-1)\pi}$$

Example

Odd Quarter-Wave Symmetry




$$\begin{aligned} b_{2n-1} &= \frac{8}{T} \int_0^{T/4} f(t) \sin[(2n-1)\omega_0 t] dt = \frac{8}{T} \int_0^{T/4} \sin[(2n-1)\omega_0 t] dt \\ &= \frac{-8}{(2n-1)\omega_0 T} \cos[(2n-1)\omega_0 t] \Big|_0^{T/4} = \frac{4}{(2n-1)\pi} \end{aligned}$$

Example

$$f(t) = \frac{4}{\pi} \left(\sin \omega_0 t + \frac{1}{3} \sin 3\omega_0 t + \frac{1}{5} \sin 5\omega_0 t + \dots \right)$$

Odd Quarter-Wave Symmetry




$$b_{2n-1} = \frac{8}{T} \int_0^{T/4} f(t) \sin[(2n-1)\omega_0 t] dt = \frac{8}{T} \int_0^{T/4} \sin[(2n-1)\omega_0 t] dt$$

$$= \frac{-8}{(2n-1)\omega_0 T} \cos[(2n-1)\omega_0 t] \Big|_0^{T/4} = \frac{4}{(2n-1)\pi}$$

Fourier Series


**Half-Range
Expansions**

Non-Periodic Function Representation




- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a **Fourier series** which is defined only in the interval $(0, \tau)$.

Without Considering Symmetry




- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a **Fourier series** which is defined only in the interval $(0, \tau)$.

Expansion Into Even Symmetry




- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a Fourier series which is defined only in the interval $(0, \tau)$.

Expansion Into Odd Symmetry




- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a Fourier series which is defined only in the interval $(0, \tau)$.

Expansion Into Half-Wave Symmetry




- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a Fourier series which is defined only in the interval $(0, \tau)$.

Expansion Into Even Quarter-Wave Symmetry



- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a **Fourier series** which is defined only in the interval $(0, \tau)$.

Expansion Into Odd Quarter-Wave Symmetry



- A non-periodic function $f(t)$ defined over $(0, \tau)$ can be expanded into a Fourier series which is defined only in the interval $(0, \tau)$.

Fourier Series

Least Mean-Square
Error Approximation

Approximation a function

Use $S_k(t) = \frac{a_0}{2} + \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t)$

to represent $f(t)$ on interval $-T/2 < t < T/2$.

Define $\varepsilon_k(t) = f(t) - S_k(t)$

$$E_k = \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt$$

Mean-Square
Error

Approximation a function

Show that using $S_k(t)$ to represent $f(t)$ has least mean-square property.

$$\begin{aligned} E_k &= \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt \\ &= \frac{1}{T} \int_{-T/2}^{T/2} \left[f(t) - \frac{a_0}{2} - \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t) \right]^2 dt \end{aligned}$$

Proven by setting $\partial E_k / \partial a_i = 0$ and $\partial E_k / \partial b_i = 0$.

Approximation a function

$$\begin{aligned} E_k &= \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt \\ &= \frac{1}{T} \int_{-T/2}^{T/2} \left[f(t) - \frac{a_0}{2} - \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t) \right]^2 dt \end{aligned}$$

$$\frac{\partial E_k}{\partial a_0} = \frac{a_0}{2} - \frac{1}{T} \int_{-T/2}^{T/2} f(t) dt = 0$$

$$\frac{\partial E_k}{\partial a_n} = a_n - \frac{2}{T} \int_{-T/2}^{T/2} f(t) \cos n\omega_0 t dt = 0$$

$$\frac{\partial E_k}{\partial b_n} = b_n - \frac{2}{T} \int_{-T/2}^{T/2} f(t) \sin n\omega_0 t dt = 0$$

Mean-Square Error

$$\begin{aligned} E_k &= \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt \\ &= \frac{1}{T} \int_{-T/2}^{T/2} \left[f(t) - \frac{a_0}{2} - \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t) \right]^2 dt \end{aligned}$$

$$E_k = \frac{1}{T} \int_{-T/2}^{T/2} [f(t)]^2 dt - \frac{a_0^2}{4} - \frac{1}{2} \sum_{n=1}^k (a_n^2 + b_n^2)$$

Mean-Square Error

$$\begin{aligned} E_k &= \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt \\ &= \frac{1}{T} \int_{-T/2}^{T/2} \left[f(t) - \frac{a_0}{2} - \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t) \right]^2 dt \end{aligned}$$

$$\frac{1}{T} \int_{-T/2}^{T/2} [f(t)]^2 dt \geq \frac{a_0^2}{4} + \frac{1}{2} \sum_{n=1}^k (a_n^2 + b_n^2)$$

Mean-Square Error

$$\begin{aligned} E_k &= \frac{1}{T} \int_{-T/2}^{T/2} [\varepsilon_k(t)]^2 dt \\ &= \frac{1}{T} \int_{-T/2}^{T/2} \left[f(t) - \frac{a_0}{2} - \sum_{n=1}^k (a_n \cos n\omega_0 t + b_n \sin n\omega_0 t) \right]^2 dt \end{aligned}$$

$$\frac{1}{T} \int_{-T/2}^{T/2} [f(t)]^2 dt = \frac{a_0^2}{4} + \frac{1}{2} \sum_{n=1}^{\infty} (a_n^2 + b_n^2)$$