

# Relation between Laplace transform & Fourier Transform

This brief note is intended for those who know a bit about Fourier transform and now wonder if Laplace and Fourier transforms are related.

To begin, we first state the definition of the Fourier transform

$$\hat{f}(\omega) = \int_{-\infty}^{\infty} f(x) e^{-j\omega x} dx$$

and its inverse

$$f(x) = \frac{1}{2\pi} \int_{-\infty}^{\infty} \hat{f}(\omega) e^{j\omega x} d\omega$$

There are two notable features. One, with Laplace transform (see Eqs.   ) below), the lower integration limit is zero, not negative infinity. Second, Laplace transform uses a transform variable in the complex plane. The transform variable in Fouier transform is a pure imaginary number, restricted to  $s = j\omega$ .

Generally, Laplace transform is for functions that are semi-infinite or piecewise continuous, as in the step or rectangular pulse functions. We also impose the condition that the function is zero at negative times:

$$f(t) = 0, \quad t < 0$$

More formally, we say the function must be of exponential order as  $t$  approaches infinity so that the transform integral converges.

A function is of exponential order if there exists (real) constants  $K, c$  and  $T$  such that

$$|f(t)| < Ke^{ct} \quad \text{for } t > T$$

or in other words, the quantity  $e^{-ct}|f(t)|$  is bounded. If  $c$  is chosen sufficiently large, the so-called *abscissa of convergence*, then  $e^{-ct}|f(t)|$  should approach zero as  $t$  approaches infinity. In terms of the Laplace transform integral  $\int_0^\infty f(t)e^{-st} dt$ , it means that the real part of  $s$  must be larger than the real part of all the poles of  $f(t)$  in order the integral to converge. Otherwise, we can force a function to be transformable with  $e^{-\gamma t}f(t)$  if we can choose  $\gamma > c$  such that  $Ke^{-(\gamma-c)t}$  approaches zero as  $t$  goes to infinity.

We now do a quick two-step to see how the definition of Laplace transform may arise from that of Fourier transform. First, we write the inverse transform of the Fourier transform of the function  $e^{-\gamma t} f(t)$ , which of course, should recover the function itself:

$$e^{-\gamma t} f(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} e^{j\omega t} d\omega \int_0^{\infty} e^{-\gamma \tau} f(\tau) e^{-j\omega \tau} d\tau$$

where we have changed the lower integration limit of the Fourier transform from  $-\infty$  to 0 because  $f(t) = 0$  when  $t < 0$ . Next, we move the exponential function  $e^{-\gamma t}$  to the RHS to go with the inverse integral and then combine the two exponential functions in the transform integral to give

$$f(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} e^{(\gamma+j\omega)t} d\omega \int_0^{\infty} f(\tau) e^{-(\gamma+j\omega)\tau} d\tau$$

From this form, we can extract the definitions of Laplace transform and its inverse:

$$F(s) = \int_0^{\infty} f(t)e^{-st} dt$$

and

$$f(t) = \frac{1}{2\pi j} \int_{\gamma-j\infty}^{\gamma+j\infty} F(s)e^{st} ds$$

where again,  $\gamma$  must be chosen to be larger than the real parts of all the poles of  $F(s)$ . Thus the path of integration of the inverse is the imaginary axis shift by the quantity  $\gamma$  to the right.